

**Apollo VPX PCIset**

**EP-5BVPXB**

**ISA PCI MainBoard**

*with Onboard PCI IDE and Super Multi-I/O.*

**TRADEMARK**

All products and company names are trademarks or registered trademarks of their respective holders.

*The specification is subject to change without notice.*

**V113**

## **Package Checklist**

Please check your package which should include all items listed below. If you find any item damaged or any missing item, please contact your supplier.

- One motherboard
- One manual
- One parallel port ribbon cable
- Two serial port ribbon cables
- One IDE ribbon cable
- One floppy ribbon cable
- One optional PS/2 mouse cable

# Contents

	page
<b>Chapter 1 - Introduction.....</b>	<b>1-1</b>
5BVPXB Board Layout .....	1-2
<b>Chapter 2 - Hardware Design .....</b>	<b>2-1</b>
2-1 Mainboard Layout .....	2-1
2-2 Connectors and Jumpers .....	2-2
2-3 System Memory Configuration .....	2-6
2-4 Integrated PCI Bridge .....	2-7
<b>Chapter 3 - Award BIOS Setup .....</b>	<b>3-1</b>
3-1 Standard CMOS Setup .....	3-2
3-3 BIOS Features Setup .....	3-2
3-3 Chipset Features Setup .....	3-6
3-4 Power Management Setup .....	3-8
3-5 PNP/PCI Configuration .....	3-10
3-6 Integrated Peripherals .....	3-12
3-7 Load Setup Defaults .....	3-14
3-8 Change Supervisor or User Password .....	3-15
3-9 IDE HDD Auto Detection .....	3-16
3-10 HDD Low Level Format .....	3-18
3-11 Save & Exit Setup .....	3-18
3-11 Exit Without Saving .....	3-18
<b>Chapter 4 - Onboard Technical Information .....</b>	<b>4-1</b>
4-1 I/O & Memory Map .....	4-1
4-2 Time & DMA Channels Map .....	4-2
4-3 Interrupt Map .....	4-2
4-4 RTC & CMOS RAM Map .....	4-3
<b>Appendix A: Post Codes .....</b>	<b>4-4</b>
<b>Appendix B: I/O Connector .....</b>	<b>4-8</b>

**NOTE :**

The **"LOAD SETUP DEFAULTS"** function loads the system default data directly from ROM and initializes the associated hardware properly. This function is necessary when you accept this mainboard, or the system CMOS data will corrupt.

<b>ROM PCI/ISA BIOS</b> <b>CMOS SETUP UTILITY</b> <b>AWARD SOFTWARE, INC.</b>	
STANDARD CMOS SETUP BIOS FEATURES SETUP CHIPSET FEATURES SETUP POWER MANAGEMENT SETUP PNP/PCI CONFIGURATION INTEGRATED PERIPHERALS LOAD SETUP DEFAULTS	SUPERVISOR PASSWORD USER PASSWORD IDE HDD AUTO DETECTION HDD LOW LEVEL FORMAT SETUP SAVING <div style="border: 2px solid black; padding: 5px; text-align: center;"> <b>Load SETUP Default (Y/N)? Y</b> </div>
ESC: QUIT F10: Save & Exit Setup	
↑ ↓ → ← : SELECT ITEM (Shift)F2 : Change Color	
Load Setup Defaults Except Standard COMS SETUP	

### LOAD SETUP DEFAULT

---

# Chapter 1

## Introduction

**The 5BVPXB** mainboard is a high performance system hardware based on Intel Pentium® processor and is equipped with four PCI slots, three standard ISA slots, Super Multi-I/O controller and dual port PCI-IDE connectors for the future expansion. The hardware dimension is 220mm x 210mm with a four-layer-design technology.

---

### Specification

- VIA Apollo VPX/97 PCIset chipset.
- Intel **Pentium**® Processor, AMD K5/K6 & Cyrix 6x86/6x86L/6x86MX operating at **90 ~ 333 MHz** and **P55C** with **321 ZIF socket 7** and scalability to accept faster Processors in the future.
- Supports up to 192 MegaBytes of DRAM (a minimum of 8 MB) on board (72-pin SIMM x 2 & 168-pin DIMM x 1). BIOS will automatically detect and configure FP/EDO and Synchronous DRAM (Refer to Chapter 2-3 System Memory Configuration).
- Supports 512KB Onboard Pipelined Burst (synchronous) L2 **Write Back/Through Cache**.
- Supports three 16 bit ISA slots and four 32 bit PCI slots and provides two independent high performance PCI IDE interfaces capable of supporting **PIO Mode 3/4 and Ultra-DMA33** devices. The **5BVPXB** supports four PCI Bus Masters and a jumperless PCI INT# control scheme which reduces configuration confusion when plugging in PCI I/O controller card(s).
- Supports **ATAPI** (e.g. **CD-ROM**) devices on both IDE interfaces.
- Supports 1 floppy port, 1 parallel port (EPP,ECP port), 2 serial ports (16550 Fast UART compatible) and 1 USB Connector.
- Supports a **PS/2** style mouse and standard AT style keyboard connectors.
- Supports Award Plug & Play BIOS. The BIOS is stored in Flash EPROM form. It provides better upgradeability for the system.
- Supports CPU Hardware sleep and SMM (System Management Mode).
- **5BVPXB** utilizes Lithium battery which provides environmental protection and longer battery life.

## 5BVPXB Layout




Figure 1-1

[Back to Top](#)

---

# Chapter 2

## Hardware design

---

### 2-1 Mainboard Layout

**The 5BVPXB** is designed with VIA Apollo VPX/97 PCIset chipset which is developed by VIA Corporation to fully support Pentium Processor PCI/ISA system. The VIA Apollo VPX/97 PCIset chipset can increase integration and improve performance designs. The chipset provides an integrated IDE controller with two high performance IDE interfaces for up to four IDE devices (hard devices, CD-ROM device, etc). The Winbond W83877F Super I/O controller provides the standard PC I/O function: floppy interface, two 16 Byte FIFO serial ports and EPP/ECP capable parallel port. The **5BVPXB** layout is shown in the previous page for user's reference. **Care must be taken** when inserting memory modules, inserting CPU or even plugging PCI card into associated slots to avoid damaging any circuits or sockets on board. A cooling fan is strongly recommended when installing Pentium/Pentium MMX/K5/K6/6x86/6x86L/MX processor due to possible overheating.

**The 5BVPXB** supports a minimum of 8MB and a maximum of 192MB of System Memory while L2 Cache is 512KB synchronous SRAM Onboard to increase system performance. (Refer to **Page 2-6 Cache Memory Configuration** for the details.)

**The 5BVPXB** supports standard Fast Page, EDO (Extended Data Out or Hyper Page Mode) or synchronous DRAM. **The 5BVPXB** provides two 72-pin SIMM and one 168-pin DIMM sites for memory expansion. The sockets support 1M x 32(4MB), 2M x 32(8MB), 4M x 32(16MB), and 8M x 32(32MB) single-sided or double-sided memory modules. The memory timing requires 70 ns Fast page devices or 60 ns EDO DRAM. (DRAM Modules may be parity [x 36] or non-parity [x 32].)

**The 5BVPXB** supports **two Onboard PCI IDE** connectors, and automatically detects IDE harddisk type by BIOS utility automatic.

**The 5BVPXB** supports Award Plug & Play BIOS for the ISA and PCI cards. The BIOS can be located in Flash EPROM which can replace BIOS code easily if necessary.

[Back to Top](#)

## 2-2 Connectors and Jumpers


This section describes all connectors and jumpers equipped in the mainboard. Please refer to **Figure 1-1** for location of each connector and jumper.


<b>J5</b>	1		<b>KeyLock</b> - Keyboard lock switch & Power LED connector. 1.Power LED(+) 2.N/C 3.GND 4.Keylock 5.GND
	5		
	1		<b>Speaker</b> - connect to the system's speaker for beeping. 1.Speaker 2.N/C 3.GND 4.GND
	4		
			<b>Reset Switch</b> - Closed to restart system.
			<b>Sleep/Resume switch</b> : Closed to enter sleep mode. A keystroke or mouse movement (mouse driver exists). Will instantly "wake up" the system.
	+		<b>Turbo LED indicator</b> - LED ON when higher speed is selected. # There is no deturbo function so that the turbo LED is always ON.
	+		<b>IDE LED indicator</b> - LED ON when Onboard PCIIDE Harddisks activate.
	+		<b>Power Saving LED indicator</b> - LED ON when system is in any Saving mode.

[Back to Top](#)




J1  1 **IrDA/ASKIR CONNECTOR**  
1.VCC  
2.NC  
3.IRX  
4.GND  
5.IRTX

J2  1 **PS/2 MOUSE CONNECTOR**  
1.RED wire  
2.BLUE wire  
3.GREEN wire  
4.NC  
5. YELLOW wire

J4  1 **The Power Supply (+12V) of the CPU Cooling FAN**  
1.GND  
2.+12V  
3.GND

[Back to Top](#)



<b>Intel Pentium<sup>®</sup> Processor / Pentium<sup>®</sup> MMX Processor / AMD K5 / K6 Installation</b>					
Clock/CPU Op.	J3	J6	J7	J8	
60/90 MHz	3-4, 5-6	1-2	1-2	1-2	
66/100 MHz	1-2, 5-6				
60/120 MHz	3-4, 5-6	2-3	1-2	1-2	
66/133 MHz	1-2, 5-6				
60/150 MHz	3-4, 5-6	2-3	2-3	1-2	
66/166 MHz	1-2, 5-6				
66/200 MHz	1-2, 5-6	1-2	2-3	1-2	
66/233 MHz	1-2, 5-6	1-2	1-2	1-2	
@ 66/266 MHz	1-2, 5-6	2-3	1-2	2-3	
@ 66/300 MHz	1-2, 5-6	2-3	2-3	2-3	
@ 66/333 MHz	1-2, 5-6	1-2	2-3	2-3	

<b>Cyrix &amp; IBM6x86/6x86L/6x86MX Installation</b>					
CPU	Clock Op.	J3	J6	J7	J8
6x86/L-PR150+	60MHz * 2	3-4, 5-6	2-3	1-2	1-2
6x86/L-PR166+	66MHz * 2	1-2, 5-6			
6x86/L-PR200+	75MHz * 2	3-4, 7-8			
6x86MX-PR166	66MHz * 2	1-2, 5-6	2-3	1-2	1-2
6x86MX-PR200	75MHz * 2	3-4, 7-8			
6x86MX-PR166	60MHz * 2.5	3-4, 5-6			
6x86MX-PR200	66MHz * 2.5	1-2, 5-6	2-3	2-3	1-2
6x86MX-PR233	75MHz * 2.5	3-4, 7-8			
@ 6x86MX-PR233	66MHz * 3	1-2, 5-6			
@ 6x86MX-PR266	75MHz * 3	3-4, 7-8	1-2	2-3	1-2
@ 6x86MX-PR266	66MHz * 3.5	1-2, 5-6			

[Back to Top](#)

<b>idt C6 Processor Installation</b>					
CPU	Clock Op.	J3	J6	J7	J8
C6-DS120	60MHz * 2	3-4, 5-6	2-3	1-2	1-2
C6-DS133	66MHz * 2	1-2, 5-6			
C6-DS180	60MHz * 3	3-4, 5-6	1-2	2-3	1-2
C6-DS200	66MHz * 3	1-2, 5-6			
@ C6-DS240	60MHz * 4	3-4, 5-6	2-3	1-2	2-3
@ C6-DS266	66MHz * 4	1-2, 5-6			
@ C6-DS300	60MHz * 5	3-4, 5-6	1-2	2-3	2-3
@ C6-DS333	66MHz * 5	1-2, 5-6			

*@ These jumper settings are reserved for the future CPU versions. When the future CPU versions are ready and suitable for this mainboard, these jumper settings will be correctly updated.*

#### J9 CPU Vcore voltage selection


1	6	1-6 : 2.1V Reserved
2	7	2-7 : 2.2V Reserved for AMD K6 in the future
3	8	3-8 : 2.8V For Intel Pentium MMX & Cyrix 6x86L
4	9	4-9 : 2.9V For AMD K6/PR2-166/200 & Cyrix 6x86MX
5	10	5-10 : 3.2V For AMD K6/PR2-233/266

*Note : J9 is for Vcore Settings of dual voltage CPUs. Please ignore the settings of single voltage CPUs. Such as Intel Pentium Processor, AMD K5, Cyrix M1 and idt C6 here.*

[Back to Top](#)


### 2-3 System Memory Configuration

The 5BVPXB supports different type of settings for the system memory. The following figures and table provides all possible memory combinations. (Please refer to **Appendix C: Memory Configuration Table** for the details).



DIMM1 BANK 0	SIMM1,2 BANK1	TOTAL Memory
SDRAM	EDO/FPDRAM	MAX. = 192MB
<div> <div>8MB</div> <div>16MB</div> <div>32MB</div> <div>64MB</div> <div>128MB</div> </div> <div>x1</div>	<div> <div>4MB</div> <div>8MB</div> <div>16MB</div> <div>32MB</div> </div> <div>x2</div>	=

- NOTE :** 1. 5BVPXB supports both Fast Page DRAM and EDO DRAM SIMMs, but they cannot be used in the same memory bank.  
 2. The KEY ZOOM of the DIMM socket is 3.3V / Unbuffered.



[Back to Top](#)

## **2-4 Integrated PCI Bridge**

The **5BVPXB** utilizes **Apollo VPX/97 PCIset** chipset to support Intel Pentium Processor PCI/ISA system. The VIA Apollo VPX/97 PCIset chipset consists of the 82C585VPX system controller (TSC), two 82C587VP Data Path (TDP) devices, and one 82C586B PCI ISA/IDE Accelerator bridge chip. It provides an interface which translates CPU cycle into PCI bus cycle, and PCI burst read/write capability. In addition, it provides high performance PCI arbitor to support four PCI Masters, Rotating Priority Mechanism, and Hidden Arbitration Scheme Minimizes Arbitration Overhead.

There are four interrupts in each PCI slot : INTA#, INTB#, INTC#, and INTD#. Since the **5BVPXB** adapts the PCI auto-configuration with the system BIOS Setup utility. When the system is turned on after adding a PCI add-in card, the BIOS automatically configure interrupts, DMA channels, I/O space, and other paramaters. You do not have to configure jumpers or worry about potential resource conflicts. Because PCI cards use the same interrupt resource as ISA cards, you must specify the interrupt used by ISA add-in cards in the BIOS Setup utility.

However, if a "Legacy card" (such as plugging a paddle card and cable into an ISA slot) is plugged in the system, modification in the **ROM SETUP UTILITY** becomes necessary. First of all, you must enter **PCI CONFIGURATION SETUP** utility from the **ROM SETUP UTILITY** main menu to set "ISA" for the **"PCI IDE IRQ MAP TO**

Secondly, you must enter the **CHIPSET FEATURES SETUP UTILITY** from the **ROM SETUP UTILITY** main menu and set "Disable" for the **"Onboard Primary PCI IDE** and the **Onboard Secondary PCI IDE**. When you plug PCI/ISA IDE cards into the system, You should select "Disabled" for the **Onboard Primary and Secondary PCI IDE** from the **CHIPSET FEATURES SETUP UTILITY** too.

You can set the system interrupt request (IRQ) on some "Legacy cards" which have on paddle card and cable. (refer to user's manual of the card) to a proper system IRQ level (In general, card's Primary is assigned to INTA and Secondary is assigned to INTB). If the card is plugged into slot 1 (marked PCI#1), you cannot use second slot (marked PCI#2) because the Secondary INT signal takes INTB from the slot (refer to Page 3-12 for circuit diagram). The user then enters the **PCI CONFIGURATION SETUP** utility from the **ROM SETUP UTILITY** main menu and set "PCI-Slot 1" for the **"PCI IDE IRQ MAP TO** (This depends on the slot # where the Legacy card is plugged).

**Back to Top**

## CHAPTER 3

### AWARD BIOS SETUP

Award's ROM BIOS provides a built-in setup program which allows user to modify the basic system configuration and hardware parameters. The modified data will be stored in a battery-backed CMOS RAM so data will be retained even when the power is turned off. In general, the information saved in the CMOS RAM stays unchanged unless there is a configuration change in the system, such as a hard drive replacement or a new device installation.

If this does happen you will need to reconfigure your configuration parameter.

### To Enter Setup Program

Power on the computer and press <Del> key immediately. This will bring you into BIOS CMOSSETUPUTILITY.

ROMPCT/ISA BIOS (2A5LDPAB) CMOS SETUP UTILITY AWARD SOFTWARE, INC.	
STANDARD CMOS SETUP BIOS FEATURES SETUP CHIPSET FEATURES SETUP POWER MANAGEMENT SETUP PNP/PCI CONFIGURATION INTEGRATED PERIPHERALS LOAD SETUP DEFAULTS	SUPERVISOR PASSWORD USER PASSWORD IDE HDD AUTO DETECTION HDD LOW LEVEL FORMAT SAVE & EXIT SETUP EXIT WITHOUT SAVING
ESC : QUIT	
F10 : Save & Exit Setup	
↑ ↓ → ← : SELECT ITEM (Shift)F2 : Change Color	
Time, Date, Hard Disk Type...	

**Figure 3-1 CMOS SETUP UTILITY**

The menu displays all major selection items. Select the item you need to reconfigure. The selection is made by moving cursor (press any direction key) to the item and press the 'Enter' key. An on-line help message is displayed at the bottom of the screen as the cursor is moving to various items which provides a better understanding of each function. When a selection is made, the menu of selected item will appear so the user can modify the associated configuration parameters.

### 3-1 STANDARD CMOS SETUP

Choose "STANDARD CMOS SETUP" in the CMOS SETUPUTILITY Menu (Fig 3-1). The STANDARD CMOS SETUP allows user to configure system setting such as the current date and time, type of hard disk drive installed, floppy drive type, and display type. Memory size is auto-detected by the BIOS and displayed for your reference. When a field is highlighted (use direction keys to move cursor and <Enter> key to select), the entries in the field will be changed by pressing <PgDn> or <PgUp> keys or user can enter new data directly from the keyboard.

ROM PCI/ISA BIOS(2A5LDPAB)									
STANDARD CMOS SETUP									
AWARD SOFTWARE, INC.									
Date (mm:dd:yy) : Wed, Apr 17 1996									
Time (hh:mm:ss) : 14 : 30 : 50									
HARD DISKS	TYPE	SIZE	CYLS	HEAD	PRECOMP	LANDZONE	SECTORS	MODE	
PrimaryMaster	: Auto	0	0	0	0	0	0	Auto	
PrimarySlave	: Auto	0	0	0	0	0	0	Auto	
Secondary Master	: Auto	0	0	0	0	0	0	Auto	
Secondary Slave	: Auto	0	0	0	0	0	0	Auto	
Drive A : 1.44M,3.5in.				Base Memory : 640K Extended Memory: 15360K Other Memory : 384K <hr/> TotalMemory : 16384K					
Drive B : None									
Floppy 3 mode Support : Disable									
Video : EGA/VGA									
Halt On : All Errors									
ESC : Quit		↑ ↓ → ← : Select Item		PU/PD/+/- : Modify					
F1 : Help		(Shift)F2 : Change Color							

**Figure 3-2 STANDARD CMOS SETUP**

**NOTE:** If the hard disk Primary Master/Slave and the Secondary Master/Slave are set as "Auto", then the hard disk size and model will be auto-detected.

**NOTE:** The "Halt On :" field is to determine when to halt the system by the BIOS if an error occurs.

### 3-2 BIOS FEATURES SETUP

Selecting the "BIOS FEATURES SETUP" option in the CMOS SETUPUTILITY menu allows user to change system related parameters in the displayed menu. This menu shows all of the manufacturer's default values of the 5BVPXB. Again, user can move the cursor by pressing direction keys and <PgDn> or <PgUp> keys to modify the parameters. Pressing [F1] key to display help message of the selected item.

This setup program also provides 2 convenient ways to load the default parameter data from BIOS[F6] or CMOS[F7] area if shown data is corrupted. This provides the system a capability to recover from any possible error.

[Back to Top](#)

ROM PCI/ISA BIOS(2A5LDPAB) BIOS FEATURES SETUP AWARD SOFTWARE, INC.				
Virus Warning	: Disabled	Video BIOS	Shadow	: Enabled
CPU Internal Cache	: Enabled	C8000-CBFFF	Shadow	: Disabled
ExternalCache	: Enabled	CC000-CFFFF	Shadow	: Disabled
Quick Power On Self Test	: Enabled	D0000-D3FFF	Shadow	: Disabled
Boot Sequence	: A, C	D4000-D7FFF	Shadow	: Disabled
Swap Floppy Drive	: Disabled	D8000-DBFFF	Shadow	: Disabled
Boot Up Floppy Seek	: Enabled	DC000-DFFFF	Shadow	: Disabled
Boot Up NumLock Status	: On			
Boot Up System Speed	: High			
Gate A20 Option	: Fast			
Typematic Rate Setting	: Disabled			
Typematic Rate (Chars/Sec)	: 6			
Type matic Delay (Msec)	: 250			
Security Option	: Setup	Esc : Quit	↑ ↓ → ← : Select Item	
PCI/VGA Palette Snoop	: Disabled	F1 : Help	PU/PD/+/- : Modify	
OS Select For DRAM > 64MB	: Non-OS2	F5 : OH Values	(Shift)F2 : Color	
		F7 : Load Setup Defaults		

**Figure 3-3 BIOS FEATURES SETUP**

**Note:** The **Security Option** contains "setup" and "system". The "setup" indicates that the password setting is for CMOS only while the "system" indicates the password setting is for both CMOS and system boot up.

- **Virus Warning:** This category flashes on the screen. During and after the system boots up, any attempt to write to the boot sector or partition table of the hard disk drive will halt the system and an error message will appear. You should then run an anti-virus program to locate the virus. Keep in mind that this feature protects only the boot sector, not the entire hard drive. Default value is Disabled.

**Enabled:** Activates automatically when the system boots up causing a warning message to appear when any attempt to access the boot sector or hard disk partition table.

**Disabled:** No warning message to appear when any attempt to access the boot sector or hard disk partition table.

- **CPU Internal Cache / External Cache:** These two categories speed up memory access. However, it depends on CPU/chipset design. The default value is Enabled. If your CPU is without Internal Cache then this item "CPU Internal Cache" will not be shown.

**Enabled:** Enable cache.

**Disable:** Disable cache.

[Back to Top](#)



- **Quick Power On Self Test:** This category speeds up Power On Self Test (POST) after you power on the computer. If it is set to Enable, BIOS will shorten or skip some checking items during POST.  
**Enabled:** Enable quick POST.  
**Disabled:** Normal POST.
- **Boot Sequence:** This category determines which drive is searched first for the O/S (Operating System). The default value is A,C.  
**A,C:** The system will search for floppy disk drive first then hard disk drive.  
**C,A:** The system will search for hard disk drive first then floppy disk drive.
- **Swap Floppy Drive:** This will swap your physical drive letters A&B if you are using two floppy disks. The default value is Disabled.  
**Enabled:** Floppy A & B will be swapped under the O/S.  
**Disabled:** Floppy A & B will be not swapped.
- **Boot Up Floppy Seek:** During Power-On-Self-Test (POST), BIOS will determine if the floppy disk drive installed is 40 or 80 tracks. Only 360K type is 40 tracks while 760K, 1.2M and 1.44M are all 80 tracks. The default value is Enabled.  
**Enabled:** BIOS searches for floppy disk drive to determine if it is 40 or 80 tracks.  
 Note that BIOS cannot tell from 720K, 1.2M or 1.44M drive type as they are all 80 tracks.  
**Disabled:** BIOS will not search for the type of floppy disk drive by track number.  
 Note that there will not be any warning message if the drive installed is 360K.
- **Boot Up NumLock Status:** The default value is On.  
**On:** Keypad is number keys.  
**Off:** Keypad is arrow keys.
- **Boot UP System Speed:** Select default system speed. The system will run at the selected speed after the system boots.  
**High:** Set the speed to high.  
**Low:** Set the speed to low.
- **Gate A20 Option:** This refers to the way the system addresses memory above 1MB (extended memory). The default value is Fast.  
**Normal:** The A20 signal is controlled by keyboard controller or chipset hardware.  
**Fast:** The A20 signal is controlled by Port 92 or chipset specific method.

[Back to Top](#)

- **Typematic Rate Setting:** This determines the typematic rate.  
**Enabled :** Enable typematic rate and typematic delay programming.  
**Disabled:** Disable typematic rate and typematic delay programming. The system BIOS will use default value of 2 items and the default is controlled by the keyboard.
  
- **Typematic Rate(Chars/Sec):**

<b>6 : 6 characters per second.</b>	<b>8 : 8 characters per second.</b>
<b>10: 10 characters per second.</b>	<b>12: 12 characters per second.</b>
<b>15: 15 characters per second.</b>	<b>20: 20 characters per second.</b>
<b>24: 24 characters per second.</b>	<b>30: 30 characters per second.</b>
  
- **Typematic Delay(Msec):** This determines the time between the first and second character displayed, when holding a key.  
250 : 250msec.  
500 : 500 msec.  
750 : 750 msec.  
1000: 1000 msec.
  
- **Security Option:** This category allows you to limit access to the system and Setup, or just to Setup. The default value is Setup.  
**System:** The system will not boot and the access to Setup will be denied if the correct password is not entered at the prompt.  
**Setup :** The system will boot, but the access to Setup will be denied if the correct password is not entered at the prompt.
  
- **PCI/VGA Palette Snoop:** This field controls the ability of a primary PCI VGA controller to share a common palette (when a snoop write cycles) with an ISA video card. The default value is Disabled.  
**Enabled:** If an ISA card connects to a PCI VGA card via the VESA connector and the ISA card connects to VGA monitor and uses the RAMDAC of PCI card, the PCI/VGA Palette Snoop is enabled.  
**Disabled:** Disable the VGA card Palette snoop function.
  
- **Video BIOS Shadow:** It determines whether video BIOS will be copied to RAM, however, it is optional from chipset design. Video Shadow will increase the video speed.  
**Enabled :** Video shadow is enabled.  
**Disabled:** Video shadow is disabled.

[Back to Top](#)

- C8000 - CBFFF Shadow:
- CC000 - CFFFF Shadow:
- D0000 - D3FFF Shadow:
- D4000 - D7FFF Shadow:
- D8000 - DBFFF Shadow:
- DC000 - DFFFF Shadow:

These categories determine whether optional ROM will be copied to RAM by 16K byte or 32K byte perunit and the size depends on the chipset.

**Enabled:** Optional shadow is enabled.

**Disabled:** Optional shadow is disabled.

### 3-3 CHIPSET FEATURES SETUP

Choose the "CHIPSET FEATURES SETUP" in the CMOS SETUP UTILITY menu to display the following menu.

ROM PCI/ISA BIOS(2A5LDPAB)	
CHIPSET FEATURES SETUP	
AWARD SOFTWARE, INC.	
DRAM Auto Configuration	: 60 ns
DRAM Timing Control	: Auto
Video BIOS Cacheable	: Enabled
System BIOS Cacheable	: Disabled
Memory Hole At 15Mb Addr.	: Disabled
Fast DRAM Decoding	: Disabled
Sustained 3T Write	: Enabled
2 Bank PBSRAM	: 3-1-1-1
Read Pipeline	: Enabled
Write Pipeline	: Enabled
Cache Timing	: Fast
Linear Burst	: Disabled
SDRAM Cycle Length	: 2
SDRAM Bank Interleave	: Disabled
Esc : Quit      ↑ ↓ → ← : Select Item F1 : Help      PU/PD/+/- : Modify F5 : Old Values      (Shift)F2 : Color F7 : Load Setup Defaults	

**Figure 3-4 CHIPSET FEATURES SETUP**

**Note:** When you insert slower memory modules in the system and set a faster timing, maybe the system will hang up.

**Back to Top**

- **DRAM Timing:** The default value is 60ns.  
*60ns* : 2 (faster) Burst Wait State, for 60~70ns Fast Page Mode/EDO DRAM.  
*70ns* : 3 (slower) Burst Wait State, for 70ns Fast Page Mode/EDO DRAM.
- **Video BIOS Cacheable: The default value is Enabled.**  
*Enabled* : Enabled the Video BIOS Cacheable to speed up the VGA Performance.  
*Disabled*: Disabled the Video BIOS Cacheable function.
- **Memory Hole at 15M-16M:** The default value is Disabled.  
*Disabled*: Normal Setting.  
*Enabled* : This field enables the main memory (15~16MB) remap to ISA BUS.

[Back to Top](#)

### 3-4 POWER MANAGEMENT SETUP

Choose the "POWER MANAGEMENT SETUP" in the CMOS SETUP UTILITY to display the following screen. This menu allows the user to modify the power management parameters and IRQ signals. In general, these parameters should not be changed unless it is absolutely necessary.

ROM PCI/ISA BIOS POWER MANAGEMENT SETUP AWARD SOFTWARE, INC.		
PowerManagement	: User Define	** Power Down & Resume Events **
PM Control by APM	: Yes	IRQ5 (LPT 2) : Primary
Video off Option	: Suspend -> Off	IRQ6 (Floppy Disk) : Disabled
Video off Method	: V/H SYNC+Blank	IRQ7 (LPT 1) : Primary
Conserve Mode	: Disabled	IRQ8 (RTC Alarm) : Disabled
Modem Use IRO	: 3	IRQ9 (IRQ2 Redir) : Primary
**PM Timers**		IRQ10 (Reserved) : Primary
HDD Power Down	: Disable	IRQ11 (Reserved) : Primary
Doze Mode	: Disable	IRQ12 (PS/2 Mouse) : Primary
Suspend Mode	: Disable	IRQ13 (Coprocessor) : Primary
**PM Events**		IRQ14 (Hard Disk) : Primary
VGA	: OFF	IRQ15 (Reserved) : Disabled
LPT & COM	: LPT/COM	
HDD & FDD	: OFF	
DMA /master	: OFF	
Primary INTR	: ON	
IRQ3 (COM 2)	: Primary	
IRQ4 (COM 1)	: Primary	
		Esc : Quit      ↑ ↓ → ← : Select Item
		F1 : Help      PU/PD/+/- : Modify
		F5 : Old Values      (Shift)F2 : Color
		F7 : Load Setup Defaults

**Figure 3-5 POWER MANAGEMENT SETUP**

Again, user can move the cursor by pressing direction keys to the field needed to be modified and press <PgDn> or <PgUp> to alter item selection. You can only change the content of **Doze Mode**, **Standby Mode**, and **Suspend Mode** when the **Power Management** is set to 'User Define'.

#### 3-4-1 The Description of the Power Management

**A. Power Management mode selection :**

**Disabled** : The system operates in NORMAL conditions (Non-GREEN) and the Power Management function is disabled.

**Max. saving:** This mode will maximize the power saving capability.

**Min. saving:** This mode will minimize the power saving capability.

**User define:** Allow user to define time-out parameters to control power saving mode. Refer to item B shown below.

[Back to Top](#)

**PMEvents:**

AWARD BIOS defines 15 PMEvents in the power management mode (Doze & suspend). The user can initialize any PM Events to be "Enable" or "Disable". When the system detects all of the enabled events, do not have any activity. It will start the system Doze timer first if the "Power Management" is not "Disabled". Once the system Doze timer is timed out, it will process doze power saving procedure by starting the system suspend timer. When the suspend timer times out, all of the CPU clock will stop by dropping system clock down to zero and remains this way until any one of the "Enabled" event occurs.

### 3-5 PNP/PCI CONFIGURATION

The PNP/PCI configuration program is for the user to modify the PCI/ISA IRQ signals when various PCI/ISA cards are inserted in the PCI or ISA slots.

**WARNING :** Any misplacing IRQ could cause system can't pick out the rescouces.

ROM PCI/ISA BIOS(2A5LDPAB) PNP/PCI CONFIGURATION AWARD SOFTWARE, INC.					
PNP Installed	:	No	CPU to PCI Write Buffer	:	Enabled
Resources Controlled By	:	Manual	PCI Dynamic Bursting	:	Enabled
Reset Configuration Data	:	Disabled	PCI Master 0 WS Write	:	Enabled
			PCI Peer Concurrency	:	Enabled
			PCI Delay Transaction	:	Disabled
IRQ-3 assigned to	:	Legacy ISA	PCI IRQ Activied By	:	Level
IRQ-4 assigned to	:	Legacy ISA	PCI IDE IRQ Map To	:	PCI-AUTO
IRQ-5 assigned to	:	PC/ISA PnP	Primary IDE INT#	:	A
IRQ-7 assigned to	:	Legacy ISA	Secondary IDE INT#	:	B
IRQ-9 assigned to	:	PC/ISA PnP			
IRQ-10 assigned to	:	PC/ISA PnP			
IRQ-11 assigned to	:	PC/ISA PnP			
IRQ-12 assigned to	:	PC/ISA PnP			
IRQ-14 assigned to	:	Legacy ISA			
IRQ-15 assigned to	:	Legacy ISA			
DMA-0 assigned to	:	PC/ISA PnP			
DMA-1 assigned to	:	PC/ISA PnP			
DMA-3 assigned to	:	PC/ISA PnP			
DMA-5 assigned to	:	PC/ISA PnP			
DMA-6 assigned to	:	PC/ISA PnP			
DMA-7 assigned to	:	PC/ISA PnP			
			ESC : Quit                    ↑ ↓ → ← : Select Item F1 : Help                    PU/PD/+/- : Modify F5 : No Change              (Shift) F2 : Color F7 : Load Setup Defaults		

**Figure 3-6 PCI CONFIGURATION SETUP**

**Back to Top**

- **Resource Controlled By:** The default value is Manual.

**Manual:** The field defines that the PNP Card's resource is controlled by manual. You can set whether IRQ-X or DMA-X is assigned to PCI/ISA PNP or Legacy ISA Cards.

**Auto:** If your ISA card and PCI card are all PNP cards. Set this field Auto. The BIOS will assign the interrupt resource automatically.

- **Reset Configuration Data:** The default value is Disabled.


**Disabled:** Normal Setting

**Enabled:** If you plug some Legacy cards in the system and record into ESCD (Extended System Configuration Data). You can set this field to be Enabled and to clear ESCD at one time, when some Legacy cards are removed.

- **PCI IDE IRQ Map To:** The default value is PCI-AUTO.

When you have true PCI card(s) plugged into the system, you will not need to change anything here in the **SETUP** program. However, if you do not know whether you are using a true PCI card, please refer to your PCI card user's manual for the details.

When you have a Legacy card (described in section 2-5) to plug into the system, a proper setting is extremely important or it may cause the system hung up. The diagram shown below tells you how the Rotating Priority Mechanism is designed.



**Figure 3-7 The Combination of PCI INT# lines**

[Back to Top](#)

### 3-6 INTEGRATED PERIPHERALS

ROM PCI/ISA BIOS(2A5LDPAB) INTEGRATED PERIPHERALS WARD SOFTWARE, INC.			
Onboard Primary PCI IDE	: Enabled	Onboard Parallel Port	: 378/IRQ7
Onboard Secondary PCI IDE	: Enabled	Onboard Parallel Mode	: ECP / EPP
IDE Prefetch Mode	: Enabled	ECP Mode Use DMA	: 3
IDE HDD Block Mode	: Enabled	Parallel Port EPP Type	: EPP1.9
IDE primary Master PIO	: Auto	Onboard USB Controller	: Disabled
IDE Primary Slave PIO	: Auto		
IDE Secondary Master PIO	: Auto		
IDE Secondary Slave PIO	: Auto		
IDE Primary Master UDMA	: Auto		
IDE Primary Slave UDMA	: Auto		
IDE Secondary Master UDMA	: Auto		
IDE Secondary Slave UDMA	: Auto		
PCI IDE Secondary Channel	: Enabled		
Onboard FDC Controller	: Enabled		
UART 2 Mode	: Standard		
		ESC : Quit	↑ ↓ → ← : Select Item
		F1 : Help	PU/PD+/- : Modify
		F5 : No Change	(Shift) F2 : Color
		F7 : Load Setup Defaults	

**Note:** If you don't use the Onboard IDE connector, then use On-card (PCI or ISA card) IDE connector. You have to set Onboard Primary PCI IDE: Disabled and Onboard Secondary PCI IDE: Disabled from CHIPSET FEATURES SETUP UTILITY.

The Onboard PCI IDE cable should be **equal to or less than 18 inches (45 cm.)**.

- **IDE HDD Block Mode:** The default value is Enabled.  
**Enabled :** Enabled IDE HDD Block Mode. The HDD transfer rate is better than Disable.  
**Disabled:** Disable IDE HDD Block Mode.
- **PCI Slot IDE 2nd Channel:** The default value is Enabled.  
**Enabled :** Enable secondary IDE port and BIOS will assign IRQ15 for this port.  
**Disabled :** Disable secondary IDE port and IRQ15 is available for other device.
- **Onboard Primary PCI IDE:** The default value is Enabled.  
**Enabled :** Enable Onboard 1st channel IDE port.  
**Disabled :** Disable Onboard 1st channel IDE port. When use On-card (PCI or ISA card) IDE connector.
- **Onboard Secondary PCI IDE:** The default value is Enabled.  
**Enabled :** Enable Onboard 2nd channel IDE port.  
**Disabled :** Disable Onboard 2nd channel IDE port When use On-card (PCI or ISA card) IDE connector.

[Back to Top](#)



- **IDE Primary Master PIO:** The default value is Auto.
  - Auto* : BIOS will automatically detect the Onboard Primary Master PCI IDE HDD Accessing mode.
  - Mode0~4* : Manually set the IDE Accessing mode.
- **IDE Primary Slave PIO:** The default value is Auto.
  - Auto* : BIOS will automatically detect the Onboard Primary Slave PCI IDE HDD Accessing mode.
  - Mode0~4* : Manually set the IDE Accessing mode.
- **IDE Secondary Master PIO:** The default value is Auto.
  - Auto* : BIOS will automatically detect the Onboard Secondary Master PCI IDE HDD Accessing mode.
  - Mode0~4* : Manually set the IDE Accessing mode.
- **IDE Secondary Slave PIO:** The default value is Auto.
  - Auto* : BIOS will automatically detect the Onboard Secondary Slave PCI IDE HDD Accessing mode.
  - Mode0~4* : Manually set the IDE Accessing mode.
- **Onboard FDC Controller:** The default value is Enabled.
  - Enabled* : Enable the Onboard floppy drive interface controller.
  - Disabled* : Disable the Onboard floppy drive interface controller, When using On-card ISA FDC's controller.
- **Onboard UART 1:** This field allows the user to select the serial port. The default value is 3F8H/IRQ4.
  - COM1:* Enable Onboard Serial port 1 and address is 3F8H/IRQ4.
  - COM2:* Enable Onboard Serial port 1 and address is 2F8H/IRQ3.
  - COM3:* Enable Onboard Serial port 1 and address is 3E8H/IRQ4.
  - COM4:* Enable Onboard Serial port 1 and address is 2E8H/IRQ3.
  - Disabled:* Disable Onboard SMC CHIP's Serial port 1.
- **Onboard UART 2:** This field allows the user to select the serial port. The default value is 2F8H/IRQ3.
  - COM1:* Enable Onboard Serial port 2 and address is 3F8H/IRQ4.
  - COM2:* Enable Onboard Serial port 2 and address is 2F8H/IRQ3.
  - COM3:* Enable Onboard Serial port 2 and address is 3E8H/IRQ4.
  - COM4:* Enable Onboard Serial port 2 and address is 2E8H/IRQ3.
  - Disabled:* Disable Onboard SMC CHIP's Serial port 2.

- **Onboard UART 2 Mode:** The default value is standard. This field allows the User to select the COM2 port that can support a serial Infrared Interface.

**Standard:** Support a Serial Infrared Interface IrDA.

**HPSIR:** Support a HP Serial Infrared Interface format.

**ASKIR:** Support a Sharp Serial Infrared Interface format.

- **Onboard Parallel port:** This field allows the user to select the LPT port. The default value is 378H/IRQ7.

**378H** : Enable Onboard LPT port and address is 378H and IRQ7

**278H** : Enable Onboard LPT port and address is 278H and IRQ5.

**3BCH** : Enable Onboard LPT port and address is 3BCH and IRQ7.

**Disabled** : Disable Onboard SMC CHIP's LPT port.

**NOTE:** Parallel Port address is 378H/3BCH that selects the routing of IRQ7 for LPT1.

Parallel Port address is 278H that selects the routing of IRQ5 for LPT1.

- **Parallel port Mode:** This field allows the user to select the parallel port mode. The default value is ECP+EPP.

**Normal** : Standard mode. IBM PC/AT Compatible bidirectional parallel port.

**EPP** : Enhanced Parallel Port mode.

**ECP** : Extended Capability Port mode.

**EPP+ECP** : ECP Mode & EPP Mode.

**ECP Mode USE DMA:** This field allows the user to select DMA1 or DMA3 for the ECP mode. The default value is DMA3.

**DMA1** : The field selects the routing of DMA1 for the ECP mode.

**DMA3** : The field selects the routing of DMA3 for the ECP mode.

---

## 3-7 LOAD SETUP DEFAULTS

The "LOAD SETUP DEFAULTS" function loads the system default data directly from ROM and initializes the associated hardware properly. This function will be necessary only when the system CMOS data is corrupted.

[Back to Top](#)

Figure 3-8 LOAD SETUP DEFAULT

### Figure 3-8 LOAD SETUP DEFAULT

**NOTE :** Either "Setup" or "System" must be selected in the "Security Option" of the BIOS FEATURES SETUP menu (Refer to Figure 3-3 for the details).

1. If CMOS is corrupted or the option is not used, a default password stored in the ROM will be used. The screen will display the following message:

Enter Password:

Press the [Enter] key to continue after proper password is given.

ConfirmPassword:

ConfirmPassword:

[Back to Top](#)

[Back to Top](#)

### 3-9 IDE HDD AUTO DETECTION

The "IDE HDD AUTO DETECTION" utility is a very useful tool especially when you do not know which kind of hard disk type you are using. You can use this utility to detect the correct disk type installed in the system automatically. **But now** you can set **HARD DISK TYPE** to **Auto** in the **STANDARD CMOS SETUP**. You do not need the "IDE HDD AUTO DETECTION" utility. The BIOS will Auto-detect the hard disk size and model on display during POST.

ROM PCI/ISA BIOS(2A5LDPAB) CMOS SETUP UTILITY AWARD SOFTWARE, INC.								
HARD DISKS	TYPE	SIZE	CYLS	HEADS	PRECOMP	LANDZONE	SECTORS	MODE
Primary Master :		343	665	16	65535	664	63	NORMAL
Primary Slave :								
Secondary Master :								
Secondary Slave :								

Select Secondary Slave Option(N=Skip) : N							
OPTIONS	SIZE	CYLS	HEAD	PRECOMP	LANDZ	SECTOR	MODE
1 (Y)	0	0	0	0	0	0	NORMAL

ESC : Skip

**Figure 3-9 IDE HDD AUTO DETECTION**

#### NOTE: HDD Modes

The Award BIOS supports 3 HDD modes : NORMAL, LBA and LARGE NORMAL mode.

Generic access mode that is neither the BIOS nor the IDE controller will make transformations during accessing.

The maximum numbers of cylinders, head & sectors for NORMAL mode are 1024, 16 and 63.

	no. Cylinder	(1024)
x	no. Head	( 16)
x	no. Sector	( 63)
x	no. per sector	( 512)
		528 Megabytes

If user sets his HDD to NORMAL mode, the maximum accessible HDD size will be 528 Megabytes even though its physical size may be greater than that!

**Note:**

To support LBA or LARGE mode of HDDs, there must be some softwares involved. All softwares are located in the Award HDD Service Routine (1NT 13h). It may fail to access a HDD with LBA (LARGE) mode selected if you are running under on Operating System which replaces the whole 1NT 13h. UNIX operating systems do not support either LBA or LARGE and must utilize the Standard mode. UNIX can support drives larger than 528MB.

---

### **3-10 HDD LOW LEVEL FORMAT**

**Interleave**

Select the interleave number of the hard disk drive that you wish to perform a low level format on. You may select from 1 to 8. Check the documentation that came with the drive for the correct interleave number, or select 0 for automatic detection.

**Auto scan bad track**

This allows the utility to scan first then format by each track.

**Start**

Press<Y>to start low level format.

---

### **3-11 SAVE & EXIT SETUP**

The "SAVE & EXIT SETUP" option will bring you back to boot up procedure with all the changes you just recorded in the CMOS RAM.

---

### **3-12 EXIT WITHOUT SAVING**

The "EXIT WITHOUT SAVING" option will bring you back to normal boot up procedure without saving any data into CMOS RAM. All old data in the CMOS will not be destroyed.

---

# Chapter 4

## Technical Information

### 4-1 I/O & MEMORY MAP

#### MEMORY MAP

Address Range	Size	Description
[00000-7FFFF]	512K	Conventional memory
[80000-9FBFF]	127K	Extended Conventional memory
[9FC00-9FFFF]	1K	Extended BIOS data area if PS/2 mouse is installed
[A0000-C7FFF]	160K	Available for Hi DOS memory
[C8000-DFFFF]	96K	Available for Hi DOS memory and adapter ROMs
[E0000-EEFFF]	60K	Available for UMB
[EF000-EFFFF]	4K	Video service routine for Monochrome & CGA adaptor
[F0000-F7FFF]	32K	BIOS CMOS setup utility
[F8000-FCFFF]	20K	BIOS runtime service routine (2)
[FD000-FDFFF]	4K	Plug and Play ESCD data area
[FE000-FFFFF]	8K	BIOS runtime service routine (1)

#### I/O MAP

[000-01F]	DMA controller.(Master)
[020-021]	INTERRUPT CONTROLLER.(Master)
[022-023]	CHIPSET control registers. I/O ports.
[040-05F]	TIMER control registers.
[060-06F]	KEYBOARD interface controller.(8042)
[070-07F]	RTC ports & CMOS I/O ports.
[080-09F]	DMA register.
[0A0-0BF]	INTERRUPT controller.(Slave)
[0C0-0DF]	DMA controller.(Slave)
[0F0-0FF]	MATH COPROCESSOR.
[1F0-1F8 ]	HARD DISK controller.
[278-27F]	PARALLEL port 2.
[2B0-2DF]	GRAPHICS adapter controller.
[2F8-2FF]	SERIAL port 2.
[360-36F]	NETWORK ports.
[378-37F]	PARALLEL port 1.
[3B0-3BF]	MONOCHROME & PARALLEL port adapter.
[3C0-3CF]	EGA adapter.
[3D0-3DF]	CGA adapter.
[3F0-3F7]	FLOPPY DISK controller.
[3F8-3FF]	SERIAL port 1.

[Back to Top](#)

## 4-2 TIME & DMA CHANNELS MAP

TIME MAP:	TIMER Channel 0	System timer interrupt.
	TIMER Channel 1	DRAM REFRESH request.
	TIMER Channel 2	SPEAKER tone generator.
DMA CHANNELS :	DMA Channel 0	Available.
	DMA Channel 1	Onboard ECP (Option).
	DMA Channel 2	FLOPPY DISK (SMC CHIP).
	DMA Channel 3	Onboard ECP (default).
	DMA Channel 4	Cascade for DMA controller 1.
	DMA Channel 5	Available.
	DMA Channel 6	Available.
	DMA Channel 7	Available.

## 4-3 INTERRUPT MAP

NMI :	Parity check error.
IRQ (H/W) :	0 System TIMER interrupt from TIMER 0.
	1 KEYBOARD output buffer full.
	2 Cascade for IRQ 8-15.
	3 SERIAL port 2.
	4 SERIAL port 1.
	5 PARALLEL port 2.
	6 FLOPPY DISK (SMC CHIP).
	7 PARALLEL port 1.
	8 RTC clock.
	9 Available.
	10 Available.
	11 Available.
	12 PS/2 Mouse.
	13 MATH coprocessor.
	14 Onboard HARD DISK(IDE1) channel.
	15 Onboard HARD DISK(IDE2) channel.

[Back to Top](#)

#### 4-4 RTC & CMOS RAM MAP

RTC & CMOS :	00	Seconds.
	01	Second alarm.
	02	Minutes.
	03	Minutes alarm.
	04	Hours.
	05	Hours alarm.
	06	Day of week.
	07	Day of month.
	08	Month.
	09	Year.
	0A	Status register A.
	0B	Status register B.
	0C	Status register C.
	0D	Status register D.
	0E	Diagnostic status byte.
	0F	Shutdown byte.
	10	FLOPPY DISK drive type byte.
	11	Reserve.
	12	HARD DISK type byte.
	13	Reserve.
	14	Equipment type.
	15	Base memory low byte.
	16	Base memory high byte.
	17	Extension memory low byte.
	18	Extension memory high byte.
	19-2d	
	2E-2F	
	30	Reserved for extension memory low bytw.
	31	Reserved for extension memory high byte.
	32	DATE CENTURY byte.
	33	INFORMATION FLAG.
	34-3F	Reserve.
	40-7F	Reserved for CHIPSET SETTING DATA.

[Back to Top](#)



## APPENDIX A: POST CODES

ISA POST codes are typically output to port address 80h.

### POST(hex) DESCRIPTION

<b>01-02</b>	Reserved.
<b>C0</b>	Turn off OEM specific cache, shadow.
<b>03</b>	<ol style="list-style-type: none"> <li>1. Initialize EISA registers (EISA BIOS only).</li> <li>2. Initialize all the standard devices with default values. Standard devices includes. <ul style="list-style-type: none"> <li>-DMA controller (8237).</li> <li>-Programmable Interrupt Controller (8259).</li> <li>-Programmable Interval Timer (8254).</li> <li>-RTC chip.</li> </ul> </li> </ol>
<b>04</b>	Reserved
<b>05</b>	<ol style="list-style-type: none"> <li>1. Keyboard Controller Self-Test.</li> <li>2. Enable Keyboard Interface.</li> </ol>
<b>06</b>	Reserved.
<b>07</b>	Verifies CMOS's basic R/W functionality.
<b>C1</b>	Auto-detection of onboard DRAM & Cache.
<b>C5</b>	Copy the BIOS from ROM into E0000-FFFFF shadow RAM so that POST will go faster.
<b>08</b>	Test the first 256K DRAM.
<b>09</b>	OEM specific cache initialization. (if needed)
<b>0A</b>	<ol style="list-style-type: none"> <li>1. Initialize the first 32 interrupt vectors with corresponding Interrupt handlers. Initialize INT no from 33-120 with Dummy (Suprious) Interrupt Handler.</li> <li>2. Issue CPUID instruction to identify CPU type.</li> <li>3. Early Power Management initialization. (OEM specific)</li> </ol>
<b>0B</b>	<ol style="list-style-type: none"> <li>1. Verify the RTC time is valid or not.</li> <li>2. Detect bad battery.</li> <li>3. Read CMOS data into BIOS stack area.</li> <li>4. PnP initializations including. (PnP BIOS only) <ul style="list-style-type: none"> <li>-Assign CSN to PnP ISA card.</li> <li>-Create resource map from ESCD.</li> </ul> </li> <li>5. Assign IO &amp; Memory for PCI devices. (PCI BIOS only)</li> </ol>

[Back to Top](#)

**POST(hex) DESCRIPTION**

<b>0C</b>	Initialization of the BIOS Data Area. (40:00 - 40:FF)
<b>0D</b>	<ol style="list-style-type: none"> <li>1.Program some of the Chipset's value according to Setup. (Early Setup Value Program)</li> <li>2.Measure CPU speed for display &amp; decide the system clock speed.</li> <li>3.Video initialization including Monochrome, CGA, EGA/VGA. If no display device found, the speaker will beep.</li> </ol>
<b>0E</b>	<ol style="list-style-type: none"> <li>1. Test video RAM. (If Monochrome display device found)</li> <li>2. Show messages including. <ul style="list-style-type: none"> <li>-Award Logo, Copyright string, BIOS Data code &amp; Part No.</li> <li>-OEM specific sign on messages.</li> <li>-Energy Star Logo. (Green BIOS ONLY)</li> <li>-CPU brand, type &amp; speed.</li> <li>-Test system BIOS checksum. (Non-Compress Version only)</li> </ul> </li> </ol>
<b>0F</b>	DMA channel 0 test.
<b>10</b>	DMA channel 1 test.
<b>11</b>	DMA page registers test.
<b>12-13</b>	Reserved.
<b>14</b>	Test 8254 Timer 0 Counter 2.
<b>15</b>	Test 8259 interrupt mask bits for channel 1.
<b>16</b>	Test 8259 interrupt mask bits for channel 2.
<b>17</b>	Reserved.
<b>19</b>	Test 8259 functionality.
<b>1A-1D</b>	Reserved.
<b>1E</b>	If EISA NVM checksum is good, execute EISA initialization. (EISA BIOS only)
<b>1F-29</b>	Reserved.
<b>30</b>	Detect Base Memory & Extended Memory Size.
<b>31</b>	<ol style="list-style-type: none"> <li>1. Test Base Memory from 256K to 640K.</li> <li>2. Test Extended Memory from 1M to the top of memory.</li> </ol>

[Back to Top](#)

**POST(hex) DESCRIPTION**

<b>32</b>	1.Display the Award Plug & Play BIOS Extension message. (PnP BIOS only) 2.Program all onboard super I/O chips (if any) including COM ports, LPT ports, FDD port ... according to setup value.
<b>33-3B</b>	Reserved.
<b>3C</b>	Set flag to allow users to enter CMOS Setup Utility.
<b>3D</b>	1.Initialize Keyboard. 2.Install PS2 mouse.
<b>3E</b>	Try to turn on Level 2 cache. Note : Some chipset may need to turn on the L2 cache in this stage. But usually, the cache is turn on later in POST 61h.
<b>3F-40</b>	Reserved.
<b>BF</b>	1.Program the rest of the Chipset's value according to Setup. (Later Setup Value Program) 2.If auto-configuration is enabled, programmed the chipset with pre-defined Values.
<b>41</b>	Initialize floppy disk drive controller.
<b>42</b>	Initialize Hard drive controller.
<b>43</b>	If it is a PnP BIOS, initialize serial & parallel ports.
<b>44</b>	Reserved.
<b>45</b>	Initialize math coprocessor.
<b>46-4D</b>	Reserved.
<b>4E</b>	If there is any error detected (such as video, kb...), show all the error messages on the screen & wait for user to press <F1> key.
<b>4F</b>	1.If password is needed, ask for password. 2.Clear the Energy Star Logo. (Green BIOS only)
<b>50</b>	Write all CMOS values currently in the BIOS stack area back into the CMOS.
<b>51</b>	Reserved.

[Back to Top](#)

## POST(hex) DESCRIPTION

- 52** 1.Initialize all ISA ROMs.  
2.Later PCI initializations. (PCI BIOS only)  
-assign IRQ to PCI devices.  
-initialize all PCI ROMs.  
3.PnP Initializations. (PnP BIOS only)  
-assign IO, Memory, IRQ & DMA to PnP ISA devices.  
-initialize all PnP ISA ROMs.  
4.Program shadows RAM according to Setup settings.  
5.Program parity according to Setup setting.  
6.Power Management Initialization.  
-Enable/Disable global PM.  
-APM interface initialization.
- 53** 1.If it is NOT a PnP BIOS, initialize serial & paralled ports.  
2.Initialize time value in BIOS data area by translate the RTC time value into a timer tick value.
- 60** Setup Virus Protection. (Boot Sector Protection) functionality according to Setup setting.
- 61** 1.Try to turn on Level 2 cache.  
Note : if L2 cache is already turned on in POST 3D, this part will be skipped.  
2.Set the boot up speed according to Setup setting.  
3.Last chance for Chipset initialization.  
4.Last chance for Power Management initialization. (Green BIOS only)  
5.Show the system configuration table.
- 62** 1.Setup daylight saving according to Setup value.  
2.Program the NUM Lock, typematic rate & typematic speed according to Setup setting.
- 63** 1.If there is any changes in the hardware configuration, update the ESCD information. (PnP BIOS only)  
2.Clear memory that have been used.  
3.Boot system via INT 19H.
- FF** System Booting. This means that the BIOS already pass the control right to the operating system.

### Unexpected Errors:


## POST(hex) DESCRIPTION

- B0** If interrupt occurs in protected mode.
- B1** Unclaimed NMI occurs.

[Back to Top](#)


## APPENDIX B: I/O CONNECTORS

### CN6 : USB CONNECTOR:




Signal Name	Pin	Pin	Signal Name
USB_VCC	1	9	Ground
USB_data0-	2	10	Ground
USB_data0+	3	11	Ground
Ground	4	12	Ground
USB_VCC	5	13	Ground
USB_data1-	6	14	Ground
USB_data1+	7	25	Ground
Ground	8	26	Ground

### CN1/COM1,CN2/COM2 : Serial Ports Connector



Signal Name	Pin	Pin	Signal Name
DCD	1	6	DSR
SIN	2	7	RTS
SOUT	3	8	CTS
DTR	4	9	RI
GND	5	10	N.C.


### CN7 : Parallel Port Connector



Signal Name	Pin	Pin	Signal Name
STROBE-	1	14	AUTO FEED-
Data Bit 0	2	15	ERROR-
Data Bit 1	3	16	INIT-
Data Bit 2	4	17	SLCT IN-
Data Bit 3	5	18	Ground
Data Bit 4	6	19	Ground
Data Bit 5	7	20	Ground
Data Bit 6	8	21	Ground
Data Bit 7	9	22	Ground
ACJ-	10	23	Ground
BUSY	11	24	Ground
PE	12	25	Ground
SLCT	13	26	N.C.


[Back to Top](#)

### CN3 : Floppy Disk Connector



Signal Name	Pin	Pin	Signal Name
Ground	1	2	FDHDIN
Ground	3	4	Reserved
Ground	5	6	FDEDIN
Ground	7	8	Index-
Ground	9	10	Motor Enable
Ground	11	12	Drive Select B-
Ground	13	14	Drive Select A-
Ground	15	16	Motor Enable
Ground	17	18	DIR-
Ground	19	20	STEP-
Ground	21	22	Write Data
Ground	23	24	Write Gate
Ground	25	26	Track 00-
Ground	27	28	Write Protect-
Ground	29	30	Read Data-
Ground	31	32	SIDE 1 SELECT-
Ground	33	34	Diskette

### CN4/CN5 : Primary, Secondary IDE Connector



Signal Name	Pin	Pin	Signal Name
Reset IDE	1	2	Ground
Host Data 7	3	4	Host Data 8
Host Data 6	5	6	Host Data 9
Host Data 5	7	8	Host Data 10
Host Data 4	9	10	Host Data 11
Host Data 3	11	12	Host Data 12
Host Data 2	13	14	Host Data 13
Host Data 1	15	16	Host Data 14
Host Data 0	17	18	Host Data 15
Ground	19	20	Key
DRQ3	21	22	Ground
I/O Write-	23	24	Ground
I/O Read-	25	26	Ground
IOCHRDY	27	28	BALE
DACK3-	29	30	Ground
IRQ14	31	32	IOCS16-
Addr 1	33	34	Ground
Addr 0	35	36	Addr 2
Chip Select 0-	37	38	Chip Select 1-
Activity	39	40	Ground

[Back to Top](#)